

855 Purchase Order Acknowledgment

X12/V5010/855 : 855 Purchase Order Acknowledgment

Author:	SPS Commerce
Company:	Academy Sports and Outdoors

Table of Contents

855	Purchase Order Acknowledgment	1
ST	Transaction Set Header	3
BAK	Beginning Segment for Purchase Order Acknowledgment	4
REF	Reference Information	5
DTM	Date/Time Reference	6
N9	Loop Extended Reference Information	7
N9	Extended Reference Information	8
MTX	Text	9
N1	Loop Party Identification	10
N1	Party Identification	11
PO1	Loop Baseline Item Data	12
PO1	Baseline Item Data	13
ACK	Loop Line Item Acknowledgment	15
ACK	Line Item Acknowledgment	16
N9	Loop Extended Reference Information	18
N9	Extended Reference Information	19
MTX	Text	20
CTT	Loop Transaction Totals	21
CTT	Transaction Totals	22
SE	Transaction Set Trailer	23

855 Purchase Order Acknowledgment

Functional Group=PR

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use
0500	REF	Reference Information	M	1			Must use
1500	DTM	Date/Time Reference	M	2			Must use
<u>LOOP ID - N9</u>					<u>5</u>		
2800	N9	Extended Reference Information	M	1			Must use
2900	MTX	Text	M	1			Must use
<u>LOOP ID - N1</u>					<u>1</u>		
3000	N1	Party Identification	M	1			Must use

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - PO1</u>					<u>100000</u>	<u>N2/0100L</u>	
0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
<u>LOOP ID - ACK</u>					<u>5</u>		
2700	ACK	Line Item Acknowledgment	O	1			Used
<u>LOOP ID - N9</u>					<u>5</u>		
3500	N9	Extended Reference Information	M	1			Must use
3600	MTX	Text	M	1			Must use

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - CTT</u>					<u>1</u>	<u>N3/0100L</u>	
0100	CTT	Transaction Totals	M	1		N3/0100	Must use
0300	SE	Transaction Set Trailer	M	1			Must use

Notes:

- 2/0100L PO102 is required.
- 2/0100 PO102 is required.
- 3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

User Note 1:*Change History*

12/17/2018

- Updated BAK02 list
- Updated ACK01 list
- Added ACK04/04/07/08 as Conditional
- Added N9 segments as Optional at both the header and line levels

1/31/2019

- Removed BAK02 qualifier AP (Product Replenishment)
- Removed line level N1 segment
- Added PO108/09 (SKU) as Optional

4/5/2019

- Removed ACK01 qualifier IB (Item Backordered)

9/13/2019

- Added DTM01 qualifier 063 and 064
- Added ACK04 qualifier 067

11/04/2019

- Removed ACK01 qualifier of DR. Line level date changes are no longer accepted.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

CodeList Summary (Total Codes: 318, Included: 1)

Code Name

855 Purchase Order Acknowledgment

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 5

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

Description: Code identifying purpose of transaction set

CodeList Summary (Total Codes: 66, Included: 1)

Code Name

00 Original

BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
-------	-----	---------------------	---	----	-----	----------

Description: Code specifying the type of acknowledgment

CodeList Summary (Total Codes: 15, Included: 6)

Code Name

AC Acknowledge - With Detail and Change
 AD Acknowledge - With Detail, No Change
 AE Acknowledge - With Exception Detail Only
 AK Acknowledge - No Detail or Change
 RD Reject with Detail
 RJ Rejected - No Detail

BAK03	324	Purchase Order Number	M	AN	1/22	Must use
-------	-----	-----------------------	---	----	------	----------

Description: Identifying number for Purchase Order assigned by the orderer/purchaser

BAK04	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

BAK09	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.
2. BAK08 is the seller's order number.
3. BAK09 is the date assigned by the sender to the acknowledgment.

REF Reference Information

Pos: 0500	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

IA Internal Vendor Number

REF02	127	Reference Identification	M	AN	1/50	Must use
-------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

DTM Date/Time Reference

Pos: 1500	Max: 2
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 4)

Code Name

- 037 Ship Not Before
- 038 Ship No Later
- 063 Do Not Deliver After
- 064 Do Not Deliver Before

DTM02	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

User Note 1:

Either Ship Window (037 and 038) or Delivery Window (064 and 063) is required.

Loop Extended Reference Information

Pos: 2800	Repeat: 5
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2800	N9	Extended Reference Information	M	1		Must use
2900	MTX	Text	M	1		Must use

User Note 1:

If Purchase Order is rejected, a note indicating why is required.

N9 Extended Reference Information

Pos: 2800	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

L1 Letters or Notes

N902	127	Reference Identification	M	AN	1/50	Must use
------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: GEN: General Note

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 2900	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use
Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	M	AN	1/4096	Must use

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Party Identification

Pos: 3000	Repeat: 1
Mandatory	
Loop: N1	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3000	N1	Party Identification	M	1		Must use

N1 Party Identification

Pos: 3000	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 3

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 1)

Code Name

ST Ship To

N103	66	Identification Code Qualifier	M	ID	1/2	Must use
------	----	-------------------------------	---	----	-----	----------

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 241, Included: 1)

Code Name

92 Assigned by Buyer or Buyer's Agent

N104	67	Identification Code	M	AN	2/80	Must use
------	----	---------------------	---	----	------	----------

Description: Code identifying a party or other code

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

Loop Baseline Item Data

Pos: 0100 Repeat:
 100000
 Mandatory
 Loop: PO1 Elements: N/A

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	M	1		Must use
2700		Loop ACK	M		5	Must use
3500		Loop N9	O		5	Used

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 7

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO102	380	Quantity	M	R	1/15	Must use
		Description: Numeric value of quantity				
PO103	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		CodeList Summary (Total Codes: 844, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		EA	Each			
PO104	212	Unit Price	M	R	1/17	Must use
		Description: Price per unit of product, service, commodity, etc.				
PO106	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		UP	UCC - 12			
PO107	234	Product/Service ID	M	AN	1/48	Must use
		Description: Identifying number for a product or service				
		User Note 1: 14 digit value is expected from the order				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		SK	Stock Keeping Unit (SKU)			
PO109	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.

5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop Line Item Acknowledgment

Pos: 2700	Repeat: 5
Mandatory	
Loop: ACK	Elements: N/A

User Option (Usage): Must use

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2700	ACK	Line Item Acknowledgment	O	1		Used

ACK Line Item Acknowledgment

Pos: 2700	Max: 1
Detail - Optional	
Loop: ACK	Elements: 7

User Option (Usage): Used

Purpose: To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

CodeList Summary (Total Codes: 26, Included: 5)

Code	Name
IA	Item Accepted
IP	Item Accepted - Price Changed
IQ	Item Accepted - Quantity Changed
IR	Item Rejected
IS	Item Accepted - Substitution Made

ACK02	380	Quantity	C	R	1/15	Used
-------	-----	----------	---	---	------	------

Description: Numeric value of quantity

User Note 1: Mandatory if ACK01 = IQ

ACK03	355	Unit or Basis for Measurement Code	C	ID	2/2	Used
-------	-----	------------------------------------	---	----	-----	------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

User Note 1: Mandatory if ACK01 = IQ

CodeList Summary (Total Codes: 844, Included: 1)

Code	Name
EA	Each

ACK04	374	Date/Time Qualifier	C	ID	3/3	Used
-------	-----	---------------------	---	----	-----	------

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 2)

Code	Name
067	Current Schedule Delivery
068	Current Schedule Ship

ACK05	373	Date	C	DT	8/8	Used
-------	-----	------	---	----	-----	------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

ACK07	235	Product/Service ID Qualifier	C	ID	2/2	Used
-------	-----	------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

User Note 1: Mandatory if ACK01 = IS

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
------------	-----------	---------------------	------------	-------------	----------------	--------------

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

UP UCC - 12

ACK08	234	Product/Service ID	C	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

User Note 1: *Mandatory if ACK01 = IS*

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.
4. P0910 - If either ACK09 or ACK10 is present, then the other is required.
5. P1112 - If either ACK11 or ACK12 is present, then the other is required.
6. P1314 - If either ACK13 or ACK14 is present, then the other is required.
7. P1516 - If either ACK15 or ACK16 is present, then the other is required.
8. P1718 - If either ACK17 or ACK18 is present, then the other is required.
9. P1920 - If either ACK19 or ACK20 is present, then the other is required.
10. P2122 - If either ACK21 or ACK22 is present, then the other is required.
11. P2324 - If either ACK23 or ACK24 is present, then the other is required.
12. P2526 - If either ACK25 or ACK26 is present, then the other is required.
13. P2728 - If either ACK27 or ACK28 is present, then the other is required.
14. C282729 - If ACK28 is present, then ACK27 and ACK29 are required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

Loop Extended Reference Information

Pos: 3500	Repeat: 5
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3500	N9	Extended Reference Information	M	1		Must use
3600	MTX	Text	M	1		Must use

User Note 1:

If an item is rejected (ACK01 = IR), a note indicating why is required.

N9 Extended Reference Information

Pos: 3500	Max: 1
Detail - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

L1 Letters or Notes

N902	127	Reference Identification	M	AN	1/50	Must use
------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: GEN: General Note

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 3600	Max: 1
Detail - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use

Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	X	AN	1/4096	Used

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Transaction Totals

Pos: 0100	Repeat: 1
Mandatory	
Loop: CTT	Elements: N/A

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	M	1		Must use

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Mandatory	
Loop: CTT	Elements: 1

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.