

Ollie's Bargain Outlet 850 Purchase Order

X12/V5010/850 : 850 Purchase Order

Version: 1.0

Author:	SPS Commerce
Company:	Ollie's Bargain Outlet
Notes:	

Table of Contents

850 Purchase Order	1
ST Transaction Set Header	3
BEG Beginning Segment for Purchase Order	4
REF Reference Information	5
PER Administrative Communications Contact	6
FOB F.O.B. Related Instructions	7
CSH Sales Requirements	8
ITD Terms of Sale/Deferred Terms of Sale	9
DTM Date/Time Reference	10
N9 Loop Extended Reference Information	11
N9 Extended Reference Information	12
MTX Text	13
N1 Loop Party Identification	14
N1 Party Identification	15
N3 Party Location	17
N4 Geographic Location	18
PO1 Loop Baseline Item Data	19
PO1 Baseline Item Data	20
CTP Loop Pricing Information	23
CTP Pricing Information	24
PID Loop Product/Item Description	25
PID Product/Item Description	26
PO4 Item Physical Details	27
SLN Loop Subline Item Detail	28
SLN Subline Item Detail	29
PID Product/Item Description	31
CTT Loop Transaction Totals	32
CTT Transaction Totals	33
AMT Monetary Amount Information	34
SE Transaction Set Trailer	35

850

Purchase Order

Functional Group=**PO**

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BEG	Beginning Segment for Purchase Order	M	1			Must use
0500	REF	Reference Information	M	3			Must use
0600	PER	Administrative Communications Contact	M	1			Must use
0800	FOB	F.O.B. Related Instructions	O	>1			Used
1100	CSH	Sales Requirements	M	1			Must use
1300	ITD	Terms of Sale/Deferred Terms of Sale	M	1			Must use
1500	DTM	Date/Time Reference	M	4			Must use
LOOP ID - N9					1000		
2950	N9	Extended Reference Information	M	1			Must use
3000	MTX	Text	M	1			Must use
LOOP ID - N1					5		
3100	N1	Party Identification	M	1			Must use
3300	N3	Party Location	C	2			Used
3400	N4	Geographic Location	M	1			Must use

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - PO1					100000	N2/0100L	
0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
LOOP ID - CTP					≥1		
0400	CTP	Pricing Information	M	1			Must use
LOOP ID - PID					1		
0500	PID	Product/Item Description	M	1			Must use
0900	PO4	Item Physical Details	M	1			Must use
LOOP ID - SLN					1000		
4700	SLN	Subline Item Detail	O	1			Used
4900	PID	Product/Item Description	M	1			Must use

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - CTT</u>					<u>1</u>	<u>N3/0100L</u>	
0100	CTT	Transaction Totals	M	1		N3/0100	Must use
0200	AMT	Monetary Amount Information	M	1		N3/0200	Must use
0300	SE	Transaction Set Trailer	M	1			Must use

Notes:

2/0100L PO102 is required.

2/0100 PO102 is required.

3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0200 If AMT is used in the summary area, then AMT01 will = TT and AMT02 will indicate total transaction amount as calculated by the sender.

Change History:

2/12/2025

When the reference field is related to the Vendor ID (REF01=IA), then the data for that field (REF02) must not exceed 6 characters.

12/16/2024

Product/Service ID values related to the following Product/Service ID Qualifiers will be rejected if they contain non-numerical data: 'EN', 'IB', 'UP'

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

CodeList Summary (Total Codes: 318, Included: 1)

Code Name

850 Purchase Order

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BEG Beginning Segment for Purchase Order

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
Description: Code identifying purpose of transaction set						
CodeList Summary (Total Codes: 66, Included: 1)						
Code Name						
00 Original						
BEG02	92	Purchase Order Type Code	M	ID	2/2	Must use
Description: Code specifying the type of Purchase Order						
CodeList Summary (Total Codes: 76, Included: 1)						
Code Name						
SA Stand-alone Order						
BEG03	324	Purchase Order Number	M	AN	1/22	Must use
Description: Identifying number for Purchase Order assigned by the orderer/purchaser						
User Note 1: Purchase Order Number is all numeric and can be up to 10 digits long.						
BEG05	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						
User Note 1: Purchase Order Date.						

Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

REF Reference Information

Pos: 0500	Max: 3
Heading - Mandatory	
Loop: N/A	Elements: 3

User Option (Usage): Must use

Purpose: To specify identifying information

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 3)

Code Name

DP Department Number

User Note 1:

Ollie's Bargain Outlet assigned Department ID - Mandatory

IA Internal Vendor Number

User Note 1:

Ollie's Bargain Outlet assigned Vendor ID - Mandatory

YD Buyer Identification

User Note 1:

Ollie's Bargain Outlet assigned Buyer ID - Mandatory

REF02	127	Reference Identification	M	AN	1/50	Must use
-------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: *When REF01=DP, REF02 will be the department number.*

When the reference field is related to the Vendor ID (REF01=IA), then the data for that field (REF02) must not exceed 6 characters.

REF03	352	Description	C	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

User Note 1: *When REF01=DP, REF03 will always be provided, REF03 will be the department name.*

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

PER Administrative Communications Contact

Pos: 0600	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code	M	ID	2/2	Must use

Description: Code identifying the major duty or responsibility of the person or group named

CodeList Summary (Total Codes: 238, Included: 1)

Code **Name**

BD Buyer Name or Department

PER02	93	Name	M	AN	1/60	Must use
-------	----	-------------	---	----	------	----------

Description: Free-form name

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

FOB F.O.B. Related Instructions

Pos: 0800	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

Purpose: To specify transportation instructions relating to shipment

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
FOB01	146	Shipment Method of Payment	M	ID	2/2	Must use

Description: Code identifying payment terms for transportation charges

CodeList Summary (Total Codes: 31, Included: 5)

Code Name

CC	Collect
DE	Per Contract
DF	Defined by Buyer and Seller

User Note 1:

No freight allowed.

MX	Mixed
PE	Prepaid and Summary Bill

FOB02	309	Location Qualifier	X	ID	1/2	Used
-------	-----	--------------------	---	----	-----	------

Description: Code identifying type of location

CodeList Summary (Total Codes: 184, Included: 1)

Code Name

OR	Origin (Shipping Point)
----	-------------------------

User Note 1:

Optional

FOB03	352	Description	O	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0302 - If FOB03 is present, then FOB02 is required.
2. C0405 - If FOB04 is present, then FOB05 is required.
3. C0706 - If FOB07 is present, then FOB06 is required.
4. C0809 - If FOB08 is present, then FOB09 is required.

Semantics:

1. FOB01 indicates which party will pay the carrier.
2. FOB02 is the code specifying transportation responsibility location.
3. FOB06 is the code specifying the title passage location.
4. FOB08 is the code specifying the point at which the risk of loss transfers. This may be different than the location specified in FOB02/FOB03 and FOB06/FOB07.

CSH Sales Requirements

Pos: 1100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 1

User Option (Usage): Must use

Purpose: To specify general conditions or requirements of the sale

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
CSH01	563	Sales Requirement Code	M	ID	1/2	Must use

Description: Code to identify a specific requirement or agreement of sale

CodeList Summary (Total Codes: 57, Included: 1)

Code Name

N No Back Order

User Note 1:

Backorders are not allowed. Please communicate short ships on the PO Acknowledgement.

Syntax Rules:

1. C0203 - If CSH02 is present, then CSH03 is required.
2. P0607 - If either CSH06 or CSH07 is present, then the other is required.
3. P0910 - If either CSH09 or CSH10 is present, then the other is required.

Semantics:

1. CSH03 is the maximum monetary amount value which the order must not exceed.
2. CSH04 is the account number to which the purchase amount is charged.
3. CSH05 is the date specified by the sender to be shown on the invoice.
4. CSH06 identifies the source of the code value in CSH07.

ITD Terms of Sale/Deferred Terms of Sale

Pos: 1300	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 1

User Option (Usage): Must use

Purpose: To specify terms of sale

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD12	352	Description	M	AN	1/80	Must use

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
2. L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
3. L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Semantics:

1. ITD15 is the percentage applied to a base amount used to determine a late payment charge.

Comments:

1. If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

User Note 1:

Payments Terms will always be included on each Purchase Order.

DTM Date/Time Reference

Pos: 1500	Max: 4
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify pertinent dates and times

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 4)

Code Name

001 Cancel After

User Note 1:

*If the PO is not delivered by this date, Ollie's reserves to cancel the PO. The cancellation process will be handled by Ollie's and not automated based on this date.
Mandatory field.*

002 Delivery Requested

User Note 1:

*PO Should be delivered on or after this date.
Mandatory field.*

037 Ship Not Before

User Note 1:

PO can be shipped starting on this date. Mandatory field.

038 Ship No Later

User Note 1:

PO must be shipped by up to and including this date. Mandatory field.

DTM02	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

Loop Extended Reference Information

Pos: 2950	Repeat: 1000
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2950	N9	Extended Reference Information	M	1		Must use
3000	MTX	Text	M	1		Must use

N9 Extended Reference Information

Pos: 2950	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

L1 Letters or Notes

N902	127	Reference Identification	M	AN	1/50	Must use
------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: N902 will contain the following 3 character code to identify the type of note which follows in MTX02.

-GEN: General Note

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 3000	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use

Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	M	AN	1/4096	Must use

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Party Identification

Pos: 3100	Repeat: 5
Mandatory	
Loop: N1	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3100	N1	Party Identification	M	1		Must use
3300	N3	Party Location	C	2		Used
3400	N4	Geographic Location	M	1		Must use

N1 Party Identification

Pos: 3100	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 5)

Code Name

BT Bill-to-Party

User Note 1:

Optional

CQ Corporate Office

User Note 1:

Optional.

SF Ship From

User Note 1:

Optional

ST Ship To

User Note 1:

Mandatory

VN Vendor

User Note 1:

Mandatory.

N102	93	Name	M	AN	1/60	Must use
------	----	------	---	----	------	----------

Description: Free-form name

User Note 1: *When N101=VN, then maximum length is 35.*

N103	66	Identification Code Qualifier	O	ID	1/2	Used
------	----	-------------------------------	---	----	-----	------

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 241, Included: 1)

Code Name

92 Assigned by Buyer or Buyer's Agent

N104	67	Identification Code	O	AN	2/80	Used
------	----	---------------------	---	----	------	------

Description: Code identifying a party or other code

User Note 1: *Mandatory when N101=BT,ST,SF*

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.

2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Party Location

Pos: 3300

Max: 2

Heading - Conditional

Loop: N1

Elements: 2

User Option (Usage): Used
Purpose: To specify the location of the named party

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
N301	166	Address Information	C	AN	1/55	Used
Description: Address information						
User Note 1: Mandatory when N101=BT or when N101=ST.						
N302	166	Address Information	O	AN	1/55	Used
Description: Address information						

N4 Geographic Location

Pos: 3400	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	M	AN	2/30	Must use
		Description: Free-form text for city name				
N402	156	State or Province Code	M	ID	2/2	Must use
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	C	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
		User Note 1: <i>Mandatory when N101=BT or when N101=ST.</i>				
N404	26	Country Code	O	ID	2/3	Used
		Description: Code identifying the country				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Baseline Item Data

Pos: 0100	Repeat: 100000
Mandatory	
Loop: PO1 Elements: N/A	

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	M	1		Must use
0400		Loop CTP	M		>1	Must use
0500		Loop PID	M		1	Must use
0900	PO4	Item Physical Details	M	1		Must use
4700		Loop SLN	O		1000	Used

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 14

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	M	AN	1/20	Must use
Description: Alphanumeric characters assigned for differentiation within a transaction set						
User Note 1: <i>The Line Sequence Number from the Purchase Order must be returned on all return transactions.</i>						
PO102	380	Quantity	M	R	1/15	Must use
Description: Numeric value of quantity						
PO103	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken						
CodeList Summary (Total Codes: 844, Included: 1)						
Code Name						
EA Each						
PO104	212	Unit Price	M	R	1/17	Must use
Description: Price per unit of product, service, commodity, etc.						
User Note 1: <i>Price per each.</i>						
PO106	235	Product/Service ID Qualifier	M	ID	2/2	Must use
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
CodeList Summary (Total Codes: 519, Included: 1)						
Code Name						
VN Vendor's (Seller's) Item Number						
PO107	234	Product/Service ID	M	AN	1/48	Must use
Description: Identifying number for a product or service						
PO108	235	Product/Service ID Qualifier	M	ID	2/2	Must use
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
CodeList Summary (Total Codes: 519, Included: 1)						
Code Name						
SK Stock Keeping Unit (SKU)						
User Note 1: <i>Ollie's Bargain Outlet assigned SKU Number.</i>						
PO109	234	Product/Service ID	M	AN	1/48	Must use

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
------------	-----------	---------------------	------------	-------------	----------------	--------------

Description: Identifying number for a product or service

PO110	235	Product/Service ID Qualifier	O	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

UP UCC - 12

User Note 1:

Only numerical data for the 12 digit UPC (also known as the Universal Product Code) will be provided.

PO111	234	Product/Service ID	O	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

PO112	235	Product/Service ID Qualifier	O	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

EN EAN/UCC - 13

User Note 1:

Only numerical data for the EAN/GTIN will be provided.

PO113	234	Product/Service ID	O	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

PO114	235	Product/Service ID Qualifier	O	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

IB International Standard Book Number (ISBN)

User Note 1:

Only numerical values will be provided for the ISBN

PO115	234	Product/Service ID	O	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.

7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop Pricing Information

Pos: 0400 Repeat: >1
Mandatory
Loop: CTP Elements: N/A

User Option (Usage): Must use

Purpose: To specify pricing information

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0400	CTP	Pricing Information	M	1		Must use

CTP Pricing Information

Pos: 0400	Max: 1
Detail - Mandatory	
Loop: CTP	Elements: 1

User Option (Usage): Must use

Purpose: To specify pricing information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTP08	782	Monetary Amount	M	R	1/18	Must use

Description: Monetary amount

User Note 1: *Extended item total*

Syntax Rules:

1. P0405 - If either CTP04 or CTP05 is present, then the other is required.
2. C0607 - If CTP06 is present, then CTP07 is required.
3. C0902 - If CTP09 is present, then CTP02 is required.
4. C1002 - If CTP10 is present, then CTP02 is required.
5. C1103 - If CTP11 is present, then CTP03 is required.

Semantics:

1. CTP07 is a multiplier factor to arrive at a final discounted price. A multiplier of .90 would be the factor if a 10% discount is given.
2. CTP08 is the rebate amount.

Comments:

1. See Figures Appendix for an example detailing the use of CTP03 and CTP04.
2. See Figures Appendix for an example detailing the use of CTP03, CTP04 and CTP07.

Loop Product/Item Description

Pos: 0500	Repeat: 1
Mandatory	
Loop: PID	Elements: N/A

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	M	1		Must use

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Mandatory	
Loop: PID	Elements: 3

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
PID01	349	Item Description Type	M	ID	1/1	Must use

Description: Code indicating the format of a description

CodeList Summary (Total Codes: 3, Included: 1)

Code Name

F Free-form

PID02	750	Product/Process Characteristic Code	M	ID	2/3	Must use
-------	-----	-------------------------------------	---	----	-----	----------

Description: Code identifying the general class of a product or process characteristic

CodeList Summary (Total Codes: 238, Included: 1)

Code Name

08 Product

User Note 1:

Mandatory

PID05	352	Description	M	AN	1/80	Must use
-------	-----	-------------	---	----	------	----------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

PO4 Item Physical Details

Pos: 0900	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 1

User Option (Usage): Must use

Purpose: To specify the physical qualities, packaging, weights, and dimensions relating to the item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO401	356	Pack	M	N0	1/6	Must use

Description: The number of inner containers, or number of eaches if there are no inner containers, per outer container

User Note 1: *Ollie's will provide their anticipated number of units within the case.*

Syntax Rules:

1. P0203 - If either PO402 or PO403 is present, then the other is required.
2. C0506 - If PO405 is present, then PO406 is required.
3. P0607 - If either PO406 or PO407 is present, then the other is required.
4. P0809 - If either PO408 or PO409 is present, then the other is required.
5. C1013 - If PO410 is present, then PO413 is required.
6. C1113 - If PO411 is present, then PO413 is required.
7. C1213 - If PO412 is present, then PO413 is required.
8. L13101112 - If PO413 is present, then at least one of PO410, PO411 or PO412 is required.
9. C1716 - If PO417 is present, then PO416 is required.
10. C1804 - If PO418 is present, then PO404 is required.

Semantics:

1. PO415 is used to indicate the relative layer of this package or range of packages within the layers of packaging. Relative Position 1 (value R1) is the innermost package.
2. PO416 is the package identifier or the beginning package identifier in a range of identifiers.
3. PO417 is the ending package identifier in a range of identifiers.
4. PO418 is the number of packages in this layer.

Comments:

1. PO403 - The "Unit or Basis for Measure Code" in this segment position is for purposes of defining the unit of measure of the "Size" identified in the PO402. For example: If the carton contains 24 12-Ounce packages, it would be described as follows: Data element 356 = "24"; Data element 357 = "12"; Data element 355 = "OZ".
2. PO413 defines the unit of measure for PO410, PO411, and PO412.

Loop Subline Item Detail

Pos: 4700 Repeat: 1000
Optional
Loop: SLN Elements: N/A

User Option (Usage): Used
Purpose: To specify product subline detail item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
4700	SLN	Subline Item Detail	O	1		Used
4900	PID	Product/Item Description	M	1		Must use

SLN Subline Item Detail

Pos: 4700	Max: 1
Detail - Optional	
Loop: SLN	Elements: 10

User Option (Usage): Used

Purpose: To specify product subline detail item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SLN01	350	Assigned Identification	M	AN	1/20	Must use
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
SLN03	662	Relationship Code	M	ID	1/1	Must use
		Description: Code indicating the relationship between entities				
		CodeList Summary (Total Codes: 5, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		I	Included			
SLN04	380	Quantity	M	R	1/15	Must use
		Description: Numeric value of quantity				
		User Note 1: <i>Case Pack Quantity</i>				
SLN05	C001	Composite Unit of Measure	M	Comp		Must use
		Description: To identify a composite unit of measure (See Figures Appendix for examples of use)				
SLN05-01	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		CodeList Summary (Total Codes: 844, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		EA	Each			
SLN09	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		VN	Vendor's (Seller's) Item Number			
		User Note 1: <i>Mandatory</i>				
SLN10	234	Product/Service ID	M	AN	1/48	Must use
		Description: Identifying number for a product or service				
SLN11	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CodeList Summary (Total Codes: 519, Included: 1)						
<u>Code</u> <u>Name</u>						
SK Stock Keeping Unit (SKU)						
User Note 1:						
<i>Ollie's Bargain Outlet assigned SKU Number. Mandatory.</i>						
SLN12	234	Product/Service ID	M	AN	1/48	Must use
Description: Identifying number for a product or service						
SLN13	235	Product/Service ID Qualifier	X	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
CodeList Summary (Total Codes: 519, Included: 1)						
<u>Code</u> <u>Name</u>						
UP UCC - 12						
SLN14	234	Product/Service ID	O	AN	1/48	Used
Description: Identifying number for a product or service						

Syntax Rules:

1. P0405 - If either SLN04 or SLN05 is present, then the other is required.
2. C0706 - If SLN07 is present, then SLN06 is required.
3. C0806 - If SLN08 is present, then SLN06 is required.
4. P0910 - If either SLN09 or SLN10 is present, then the other is required.
5. P1112 - If either SLN11 or SLN12 is present, then the other is required.
6. P1314 - If either SLN13 or SLN14 is present, then the other is required.
7. P1516 - If either SLN15 or SLN16 is present, then the other is required.
8. P1718 - If either SLN17 or SLN18 is present, then the other is required.
9. P1920 - If either SLN19 or SLN20 is present, then the other is required.
10. P2122 - If either SLN21 or SLN22 is present, then the other is required.
11. P2324 - If either SLN23 or SLN24 is present, then the other is required.
12. P2526 - If either SLN25 or SLN26 is present, then the other is required.
13. P2728 - If either SLN27 or SLN28 is present, then the other is required.

Semantics:

1. SLN01 is the identifying number for the subline item.
2. SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
3. SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
4. SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
3. SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

PID Product/Item Description

Pos: 4900	Max: 1
Detail - Mandatory	
Loop: SLN	Elements: 3

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>				
PID01	349	Item Description Type	M	ID	1/1	Must use				
Description: Code indicating the format of a description										
CodeList Summary (Total Codes: 3, Included: 1)										
<table><tr><th><u>Code</u></th><th><u>Name</u></th></tr><tr><td>F</td><td>Free-form</td></tr></table>							<u>Code</u>	<u>Name</u>	F	Free-form
<u>Code</u>	<u>Name</u>									
F	Free-form									
PID02	750	Product/Process Characteristic Code	M	ID	2/3	Must use				
Description: Code identifying the general class of a product or process characteristic										
CodeList Summary (Total Codes: 238, Included: 1)										
<table><tr><th><u>Code</u></th><th><u>Name</u></th></tr><tr><td>08</td><td>Product</td></tr></table>							<u>Code</u>	<u>Name</u>	08	Product
<u>Code</u>	<u>Name</u>									
08	Product									
PID05	352	Description	X	AN	1/80	Used				
Description: A free-form description to clarify the related data elements and their content										

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

Loop Transaction Totals

Pos: 0100	Repeat: 1
Mandatory	
Loop: CTT	Elements: N/A

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	M	1		Must use
0200	AMT	Monetary Amount Information	M	1		Must use

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Mandatory	
Loop: CTT	Elements: 2

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use
Description: Total number of line items in the transaction set						
CTT02	347	Hash Total	M	R	1/10	Must use
Description: Sum of values of the specified data element. All values in the data element will be summed without regard to decimal points (explicit or implicit) or signs. Truncation will occur on the left most digits if the sum is greater than the maximum size of the hash total of the data element. Example: -.0018 First occurrence of value being hashed. .18 Second occurrence of value being hashed. 1.8 Third occurrence of value being hashed. 18.01 Fourth occurrence of value being hashed. 18E2 Fifth occurrence of value being hashed. ----- 1873 Hash Total						

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

AMT Monetary Amount Information

Pos: 0200	Max: 1
Summary - Mandatory	
Loop: CTT	Elements: 2

User Option (Usage): Must use
Purpose: To indicate the total monetary amount

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage				
AMT01	522	Amount Qualifier Code	M	ID	1/3	Must use				
Description: Code to qualify amount										
CodeList Summary (Total Codes: 1765, Included: 1)										
<table><tr><th>Code</th><th>Name</th></tr><tr><td>TT</td><td>Total Transaction Amount</td></tr></table>							Code	Name	TT	Total Transaction Amount
Code	Name									
TT	Total Transaction Amount									
AMT02	782	Monetary Amount	M	R	1/18	Must use				
Description: Monetary amount										

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
Description: Total number of segments included in a transaction set including ST and SE segments						
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Comments:

1. SE is the last segment of each transaction set.