

Ollie's Bargain Outlet 860 Purchase Order Change Request

X12/V5010/860 : 860 Purchase Order Change Request

Version: 1.0

Author:	SPS Commerce
Company:	Ollie's Bargain Outlet
Publication:	9/21/2023
Modified:	10/8/2025
Notes:	

Table of Contents

860 Purchase Order Change Request - Buyer Initiated	1
ST Transaction Set Header	3
BCH Beginning Segment for Purchase Order Change	4
REF Reference Information	5
PER Administrative Communications Contact	6
FOB F.O.B. Related Instructions	7
CSH Sales Requirements	8
ITD Terms of Sale/Deferred Terms of Sale	9
DTM Date/Time Reference	10
N9 Loop Extended Reference Information	11
N9 Extended Reference Information	12
MTX Text	13
N1 Loop Party Identification	14
N1 Party Identification	15
N3 Party Location	17
N4 Geographic Location	18
POC Loop Line Item Change	19
POC Line Item Change	20
CTP Pricing Information	23
PID Loop Product/Item Description	24
PID Product/Item Description	25
PO4 Item Physical Details	26
N9 Loop Extended Reference Information	27
N9 Extended Reference Information	28
MTX Text	29
SLN Loop Subline Item Detail	30
SLN Subline Item Detail	31
PID Product/Item Description	33
CTT Loop Transaction Totals	34
CTT Transaction Totals	35
AMT Monetary Amount Information	36
SE Transaction Set Trailer	37

860 Purchase Order Change Request - Buyer Initiated

Functional Group=**PC**

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Change Request - Buyer Initiated Transaction Set (860) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide the information required for the customary and established business and industry practice relative to a purchase order change. This transaction can be used: (1) by a buyer to request a change to a previously submitted purchase order or (2) by a buyer to confirm acceptance of a purchase order change initiated by the seller or by mutual agreement of the two parties.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BCH	Beginning Segment for Purchase Order Change	M	1			Must use
0500	REF	Reference Information	M	3			Must use
0600	PER	Administrative Communications Contact	M	1			Must use
0800	FOB	F.O.B. Related Instructions	O	>1			Used
1100	CSH	Sales Requirements	M	1			Must use
1300	ITD	Terms of Sale/Deferred Terms of Sale	M	5			Must use
1500	DTM	Date/Time Reference	M	4			Must use
LOOP ID - N9					1000		
2850	N9	Extended Reference Information	O	1			Used
2900	MTX	Text	O	>1			Used
LOOP ID - N1					5		
3000	N1	Party Identification	M	1			Must use
3200	N3	Party Location	C	2			Used
3300	N4	Geographic Location	M	>1			Must use

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
LOOP ID - POC					>1		
0100	POC	Line Item Change	M	1			Must use
0400	CTP	Pricing Information	M	>1			Must use
LOOP ID - PID					1000		
0500	PID	Product/Item Description	M	1			Must use
0900	PO4	Item Physical Details	O	>1			Used
LOOP ID - N9					1000		
3200	N9	Extended Reference Information	M	1			Must use
3260	MTX	Text	M	>1			Must use
LOOP ID - SLN					1000		
4600	SLN	Subline Item Detail	O	1			Used

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
4800	PID	Product/Item Description	O	1000			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - CTT</u>					<u>1</u>	<u>N3/0100L</u>	
0100	CTT	Transaction Totals	M	1		N3/0100	Must use
0200	AMT	Monetary Amount Information	O	5			Used
0300	SE	Transaction Set Trailer	M	1			Must use

Notes:

3/0100L Number of line items (CTT01) is the accumulation of the number of POC segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (POC03) for each POC segment.

3/0100 Number of line items (CTT01) is the accumulation of the number of POC segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (POC03) for each POC segment.

Change History:

2/12/2025

When the reference field is related to the Vendor ID (REF01=IA), then the data for that field (REF02) must not exceed 6 characters.

12/16/2024

Ollie's Bargain Outlet will only provide numerical data values for the Product/Service ID related to the following Product/Service ID Qualifiers: 'EN', 'IB', 'UP'

9/10/2024

Removal of SLN06 and SLN08. These are not being used by Ollie's.

9/22/2025

Corrected BCH01 codes to the currently used 01 and 05 values.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 3

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
Description: Code uniquely identifying a Transaction Set All valid standard codes are used. (Total Codes: 318)						
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						
ST03	1705	Implementation Convention Reference	O	AN	1/35	Used
Description: Reference assigned to identify Implementation Convention						

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BCH Beginning Segment for Purchase Order Change

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Change Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BCH01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
Description: Code identifying purpose of transaction set						
CodeList Summary (Total Codes: 66, Included: 2)						
<u>Code</u> <u>Name</u>						
01 Cancellation						
05 Replace						
BCH02	92	Purchase Order Type Code	M	ID	2/2	Must use
Description: Code specifying the type of Purchase Order						
CodeList Summary (Total Codes: 76, Included: 1)						
<u>Code</u> <u>Name</u>						
SA Stand-alone Order						
BCH03	324	Purchase Order Number	M	AN	1/22	Must use
Description: Identifying number for Purchase Order assigned by the orderer/purchaser						
BCH06	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						
User Note 1: PO Change Date						

Semantics:

1. BCH06 is the date assigned by the purchaser to purchase order.
2. BCH09 is the seller's order number.
3. BCH10 is the date assigned by the sender to the acknowledgment.
4. BCH11 is the date of the purchase order change request.

REF Reference Information

Pos: 0500	Max: 3
Heading - Mandatory	
Loop: N/A	Elements: 3

User Option (Usage): Must use

Purpose: To specify identifying information

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 3)

Code Name

DP Department Number

User Note 1:

Ollie's Bargain Outlet assigned Department ID - Mandatory

IA Internal Vendor Number

User Note 1:

Ollie's Bargain Outlet assigned Vendor ID - Mandatory

YD Buyer Identification

User Note 1:

Ollie's Bargain Outlet assigned Buyer ID - Mandatory

REF02	127	Reference Identification	M	AN	1/50	Must use
-------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: *When REF01=DP, REF02 will be the department number.*

When the reference field is related to the Vendor ID (REF01=IA), then the data for that field (REF02) must not exceed 6 characters.

REF03	352	Description	C	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

User Note 1: *When REF01=DP, REF03 will always be provided, REF03 will be the department name.*

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

PER Administrative Communications Contact

Pos: 0600	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To identify a person or office to whom administrative communications should be directed

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	Contact Function Code	M	ID	2/2	Must use

Description: Code identifying the major duty or responsibility of the person or group named

CodeList Summary (Total Codes: 238, Included: 1)

Code Name

BD Buyer Name or Department

PER02	93	Name	O	AN	1/60	Used
-------	----	------	---	----	------	------

Description: Free-form name

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

FOB F.O.B. Related Instructions

Pos: 0800	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

Purpose: To specify transportation instructions relating to shipment

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
FOB01	146	Shipment Method of Payment	M	ID	2/2	Must use

Description: Code identifying payment terms for transportation charges

CodeList Summary (Total Codes: 31, Included: 5)

Code Name

CC	Collect
DE	Per Contract
DF	Defined by Buyer and Seller

User Note 1:

No freight allowed.

MX	Mixed
PE	Prepaid and Summary Bill

FOB02	309	Location Qualifier	X	ID	1/2	Used
-------	-----	--------------------	---	----	-----	------

Description: Code identifying type of location

CodeList Summary (Total Codes: 184, Included: 1)

Code Name

OR	Origin (Shipping Point)
----	-------------------------

FOB03	352	Description	O	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0302 - If FOB03 is present, then FOB02 is required.
2. C0405 - If FOB04 is present, then FOB05 is required.
3. C0706 - If FOB07 is present, then FOB06 is required.
4. C0809 - If FOB08 is present, then FOB09 is required.

Semantics:

1. FOB01 indicates which party will pay the carrier.
2. FOB02 is the code specifying transportation responsibility location.
3. FOB06 is the code specifying the title passage location.
4. FOB08 is the code specifying the point at which the risk of loss transfers. This may be different than the location specified in FOB02/FOB03 and FOB06/FOB07.

CSH Sales Requirements

Pos: 1100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 1

User Option (Usage): Must use

Purpose: To specify general conditions or requirements of the sale

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
CSH01	563	Sales Requirement Code	M	ID	1/2	Must use

Description: Code to identify a specific requirement or agreement of sale

CodeList Summary (Total Codes: 57, Included: 1)

Code Name

N No Back Order

User Note 1:

Backorders are not allowed. Please communicate short ships on the PO Acknowledgement.

Syntax Rules:

1. C0203 - If CSH02 is present, then CSH03 is required.
2. P0607 - If either CSH06 or CSH07 is present, then the other is required.
3. P0910 - If either CSH09 or CSH10 is present, then the other is required.

Semantics:

1. CSH03 is the maximum monetary amount value which the order must not exceed.
2. CSH04 is the account number to which the purchase amount is charged.
3. CSH05 is the date specified by the sender to be shown on the invoice.
4. CSH06 identifies the source of the code value in CSH07.

ITD Terms of Sale/Deferred Terms of Sale

Pos: 1300	Max: 5
Heading - Mandatory	
Loop: N/A	Elements: 1

User Option (Usage): Must use

Purpose: To specify terms of sale

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD12	352	Description	M	AN	1/80	Must use

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
2. L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
3. L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Semantics:

1. ITD15 is the percentage applied to a base amount used to determine a late payment charge.

Comments:

1. If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

DTM Date/Time Reference

Pos: 1500	Max: 4
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To specify pertinent dates and times

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 4)

Code Name

001 Cancel After

User Note 1:

*If the PO is not delivered by this date, Ollie's reserves to cancel the PO. The cancellation process will be handled by Ollie's and not automated based on this date.
Mandatory field.*

002 Delivery Requested

User Note 1:

*PO Should be delivered on or after this date.
Mandatory field.*

037 Ship Not Before

User Note 1:

PO can be shipped starting on this date. Mandatory field.

038 Ship No Later

User Note 1:

PO must be shipped by up to and including this date. Mandatory field.

DTM02	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

Loop Extended Reference Information

Pos: 2850	Repeat: 1000
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2850	N9	Extended Reference Information	O	1		Used
2900	MTX	Text	O	>1		Used

N9 Extended Reference Information

Pos: 2850	Max: 1
Heading - Optional	
Loop: N9	Elements: 2

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

L1 Letters or Notes

N902	127	Reference Identification	X	AN	1/50	Used
------	-----	--------------------------	---	----	------	------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: N902 will contain the following 3 character code to identify the type of note which follows in MTX02:

GEN: General Note

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 2900	Max: >1
Heading - Optional	
Loop: N9	Elements: 1

User Option (Usage): Used

Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	M	AN	1/4096	Must use

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Party Identification

Pos: 3000	Repeat: 5
Mandatory	
Loop: N1	Elements: N/A

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3000	N1	Party Identification	M	1		Must use
3200	N3	Party Location	C	2		Used
3300	N4	Geographic Location	M	>1		Must use

N1 Party Identification

Pos: 3000	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 5)

Code Name

BT Bill-to-Party

User Note 1:

Optional

CQ Corporate Office

User Note 1:

Optional.

SF Ship From

User Note 1:

Optional

ST Ship To

User Note 1:

Mandatory

VN Vendor

User Note 1:

Mandatory.

N102	93	Name	M	AN	1/60	Must use
------	----	------	---	----	------	----------

Description: Free-form name

User Note 1: *When N101=VN, then maximum length is 35.*

N103	66	Identification Code Qualifier	O	ID	1/2	Used
------	----	-------------------------------	---	----	-----	------

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 241, Included: 1)

Code Name

92 Assigned by Buyer or Buyer's Agent

N104	67	Identification Code	O	AN	2/80	Used
------	----	---------------------	---	----	------	------

Description: Code identifying a party or other code

User Note 1: *Mandatory when N101=BT,ST,SF*

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.

2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Party Location

Pos: 3200

Max: 2

Heading - Conditional

Loop: N1

Elements: 2

User Option (Usage): Used
Purpose: To specify the location of the named party

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
N301	166	Address Information	C	AN	1/55	Used
Description: Address information						
User Note 1: Mandatory when N101=BT or when N101=ST.						
N302	166	Address Information	O	AN	1/55	Used
Description: Address information						

N4 Geographic Location

Pos: 3300	Max: >1
Heading - Mandatory	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	M	AN	2/30	Must use
		Description: Free-form text for city name				
N402	156	State or Province Code	M	ID	2/2	Must use
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	C	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
		User Note 1: <i>Mandatory when N101=BT or when N101=ST.</i>				
N404	26	Country Code	O	ID	2/3	Used
		Description: Code identifying the country				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Line Item Change

Pos: 0100 Repeat: >1
Mandatory
Loop: POC Elements: N/A

User Option (Usage): Must use

Purpose: To specify changes to a line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	POC	Line Item Change	M	1		Must use
0400	CTP	Pricing Information	M	>1		Must use
0500		Loop PID	M		1000	Must use
0900	PO4	Item Physical Details	O	>1		Used
3200		Loop N9	O		1000	Used
4600		Loop SLN	O		1000	Used

POC Line Item Change

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: POC	Elements: 15

User Option (Usage): Must use

Purpose: To specify changes to a line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
POC01	350	Assigned Identification	M	AN	1/20	Must use
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
POC02	670	Change or Response Type Code	M	ID	2/2	Must use
		Description: Code specifying the type of change to the line item				
		CodeList Summary (Total Codes: 30, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		RZ	Replace All Values			
POC03	380	Quantity	M	R	1/15	Must use
		Description: Numeric value of quantity				
POC05	C001	Composite Unit of Measure	M	Comp		Must use
		Description: To identify a composite unit of measure (See Figures Appendix for examples of use)				
POC05-01	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		CodeList Summary (Total Codes: 844, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		EA	Each			
POC06	212	Unit Price	M	R	1/17	Must use
		Description: Price per unit of product, service, commodity, etc.				
POC08	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		VN	Vendor's (Seller's) Item Number			
POC09	234	Product/Service ID	M	AN	1/48	Must use
		Description: Identifying number for a product or service				
POC10	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CodeList Summary (Total Codes: 519, Included: 1)						
<u>Code</u> <u>Name</u>						
SK Stock Keeping Unit (SKU)						
User Note 1:						
<i>Ollie's Bargain Outlet assigned SKU Number.</i>						
POC11	234	Product/Service ID	M	AN	1/48	Must use
Description: Identifying number for a product or service						
POC12	235	Product/Service ID Qualifier	O	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
CodeList Summary (Total Codes: 519, Included: 1)						
<u>Code</u> <u>Name</u>						
UP UCC - 12						
User Note 1:						
<i>Only numerical data for the 12 digit UPC (also known as the Universal ProductCode) will be provided..</i>						
POC13	234	Product/Service ID	O	AN	1/48	Used
Description: Identifying number for a product or service						
POC14	235	Product/Service ID Qualifier	O	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
CodeList Summary (Total Codes: 519, Included: 1)						
<u>Code</u> <u>Name</u>						
EN EAN/UCC - 13						
User Note 1:						
<i>Only numerical data for the EAN/GTIN will be provided.</i>						
POC15	234	Product/Service ID	O	AN	1/48	Used
Description: Identifying number for a product or service						
POC16	235	Product/Service ID Qualifier	O	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
CodeList Summary (Total Codes: 519, Included: 1)						
<u>Code</u> <u>Name</u>						
IB International Standard Book Number (ISBN)						
User Note 1:						
<i>Only numerical values will be provided for the ISBN</i>						
POC17	234	Product/Service ID	O	AN	1/48	Used
Description: Identifying number for a product or service						

Syntax Rules:

1. P0305 - If either POC03 or POC05 is present, then the other is required.
2. C0405 - If POC04 is present, then POC05 is required.
3. C0706 - If POC07 is present, then POC06 is required.
4. P0809 - If either POC08 or POC09 is present, then the other is required.
5. P1011 - If either POC10 or POC11 is present, then the other is required.
6. P1213 - If either POC12 or POC13 is present, then the other is required.
7. P1415 - If either POC14 or POC15 is present, then the other is required.
8. P1617 - If either POC16 or POC17 is present, then the other is required.
9. P1819 - If either POC18 or POC19 is present, then the other is required.
10. P2021 - If either POC20 or POC21 is present, then the other is required.
11. P2223 - If either POC22 or POC23 is present, then the other is required.
12. P2425 - If either POC24 or POC25 is present, then the other is required.
13. P2627 - If either POC26 or POC27 is present, then the other is required.

Semantics:

1. POC01 is the purchase order line item identification.
2. POC03 is quantity ordered.

CTP Pricing Information

Pos: 0400	Max: >1
Detail - Mandatory	
Loop: POC	Elements: 1

User Option (Usage): Must use

Purpose: To specify pricing information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTP08	782	Monetary Amount	M	R	1/18	Must use

Description: Monetary amount

User Note 1: *Extended item total*

Syntax Rules:

1. P0405 - If either CTP04 or CTP05 is present, then the other is required.
2. C0607 - If CTP06 is present, then CTP07 is required.
3. C0902 - If CTP09 is present, then CTP02 is required.
4. C1002 - If CTP10 is present, then CTP02 is required.
5. C1103 - If CTP11 is present, then CTP03 is required.

Semantics:

1. CTP07 is a multiplier factor to arrive at a final discounted price. A multiplier of .90 would be the factor if a 10% discount is given.
2. CTP08 is the rebate amount.

Comments:

1. See Figures Appendix for an example detailing the use of CTP03 and CTP04.
2. See Figures Appendix for an example detailing the use of CTP03, CTP04 and CTP07.

Loop Product/Item Description

Pos: 0500	Repeat: 1000
Mandatory	
Loop: PID	Elements: N/A

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	M	1		Must use

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Mandatory	
Loop: PID	Elements: 3

User Option (Usage): Must use

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use
Description: Code indicating the format of a description						
CodeList Summary (Total Codes: 3, Included: 1)						
<u>Code</u> <u>Name</u>						
F Free-form						
PID02	750	Product/Process Characteristic Code	M	ID	2/3	Must use
Description: Code identifying the general class of a product or process characteristic						
CodeList Summary (Total Codes: 238, Included: 1)						
<u>Code</u> <u>Name</u>						
08 Product						
PID05	352	Description	M	AN	1/80	Must use
Description: A free-form description to clarify the related data elements and their content						

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

PO4 Item Physical Details

Pos: 0900	Max: >1
Detail - Optional	
Loop: POC	Elements: 1

User Option (Usage): Used

Purpose: To specify the physical qualities, packaging, weights, and dimensions relating to the item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO401	356	Pack	O	N0	1/6	Used

Description: The number of inner containers, or number of eaches if there are no inner containers, per outer container

Syntax Rules:

1. P0203 - If either PO402 or PO403 is present, then the other is required.
2. C0506 - If PO405 is present, then PO406 is required.
3. P0607 - If either PO406 or PO407 is present, then the other is required.
4. P0809 - If either PO408 or PO409 is present, then the other is required.
5. C1013 - If PO410 is present, then PO413 is required.
6. C1113 - If PO411 is present, then PO413 is required.
7. C1213 - If PO412 is present, then PO413 is required.
8. L13101112 - If PO413 is present, then at least one of PO410, PO411 or PO412 is required.
9. C1716 - If PO417 is present, then PO416 is required.
10. C1804 - If PO418 is present, then PO404 is required.

Semantics:

1. PO415 is used to indicate the relative layer of this package or range of packages within the layers of packaging. Relative Position 1 (value R1) is the innermost package.
2. PO416 is the package identifier or the beginning package identifier in a range of identifiers.
3. PO417 is the ending package identifier in a range of identifiers.
4. PO418 is the number of packages in this layer.

Comments:

1. PO403 - The "Unit or Basis for Measure Code" in this segment position is for purposes of defining the unit of measure of the "Size" identified in the PO402. For example: If the carton contains 24 12-Ounce packages, it would be described as follows: Data element 356 = "24"; Data element 357 = "12"; Data element 355 = "OZ".
2. PO413 defines the unit of measure for PO410, PO411, and PO412.

Loop Extended Reference Information

Pos: 3200	Repeat: 1000
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3200	N9	Extended Reference Information	M	1		Must use
3260	MTX	Text	M	>1		Must use

N9 Extended Reference Information

Pos: 3200	Max: 1
Detail - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1731, Included: 1)

Code Name

L1 Letters or Notes

N902	127	Reference Identification	M	AN	1/50	Must use
------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

User Note 1: N902 will contain the following 3 character code to identify the type of note which follows in MTX02:
GEN: General Note

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 3260	Max: >1
Detail - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use

Purpose: To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	M	AN	1/4096	Must use

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Subline Item Detail

Pos: 4600 Repeat: 1000
Optional
Loop: SLN Elements: N/A

User Option (Usage): Used

Purpose: To specify product subline detail item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
4600	SLN	Subline Item Detail	O	1		Used
4800	PID	Product/Item Description	O	1000		Used

SLN Subline Item Detail

Pos: 4600	Max: 1
Detail - Optional	
Loop: SLN	Elements: 11

User Option (Usage): Used

Purpose: To specify product subline detail item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SLN01	350	Assigned Identification	M	AN	1/20	Must use
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
SLN02	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
SLN03	662	Relationship Code	M	ID	1/1	Must use
		Description: Code indicating the relationship between entities				
		CodeList Summary (Total Codes: 5, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		I	Included			
SLN04	380	Quantity	M	R	1/15	Must use
		Description: Numeric value of quantity				
SLN05	C001	Composite Unit of Measure	M	Comp		Must use
		Description: To identify a composite unit of measure (See Figures Appendix for examples of use)				
SLN05-01	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		CodeList Summary (Total Codes: 844, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		EA	Each			
SLN09	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		CodeList Summary (Total Codes: 519, Included: 1)				
		<u>Code</u>	<u>Name</u>			
		VN	Vendor's (Seller's) Item Number			
SLN10	234	Product/Service ID	M	AN	1/48	Must use
		Description: Identifying number for a product or service				
SLN11	235	Product/Service ID Qualifier	M	ID	2/2	Must use
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
------------	-----------	---------------------	------------	-------------	----------------	--------------

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

SK Stock Keeping Unit (SKU)

User Note 1:

Ollie's Bargain Outlet assigned SKU Number.

SLN12	234	Product/Service ID	M	AN	1/48	Must use
-------	-----	---------------------------	---	----	------	----------

Description: Identifying number for a product or service

SLN13	235	Product/Service ID Qualifier	O	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 519, Included: 1)

Code Name

UP UCC - 12

SLN14	234	Product/Service ID	O	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

Syntax Rules:

1. P0405 - If either SLN04 or SLN05 is present, then the other is required.
2. C0706 - If SLN07 is present, then SLN06 is required.
3. C0806 - If SLN08 is present, then SLN06 is required.
4. P0910 - If either SLN09 or SLN10 is present, then the other is required.
5. P1112 - If either SLN11 or SLN12 is present, then the other is required.
6. P1314 - If either SLN13 or SLN14 is present, then the other is required.
7. P1516 - If either SLN15 or SLN16 is present, then the other is required.
8. P1718 - If either SLN17 or SLN18 is present, then the other is required.
9. P1920 - If either SLN19 or SLN20 is present, then the other is required.
10. P2122 - If either SLN21 or SLN22 is present, then the other is required.
11. P2324 - If either SLN23 or SLN24 is present, then the other is required.
12. P2526 - If either SLN25 or SLN26 is present, then the other is required.
13. P2728 - If either SLN27 or SLN28 is present, then the other is required.

Semantics:

1. SLN01 is the identifying number for the subline item.
2. SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
3. SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
4. SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
3. SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

PID Product/Item Description

Pos: 4800	Max: 1000
Detail - Optional	
Loop: SLN	Elements: 3

User Option (Usage): Used

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use
Description: Code indicating the format of a description						
CodeList Summary (Total Codes: 3, Included: 1)						
<u>Code</u> <u>Name</u>						
F Free-form						
PID02	750	Product/Process Characteristic Code	O	ID	2/3	Used
Description: Code identifying the general class of a product or process characteristic						
CodeList Summary (Total Codes: 238, Included: 1)						
<u>Code</u> <u>Name</u>						
08 Product						
PID05	352	Description	X	AN	1/80	Used
Description: A free-form description to clarify the related data elements and their content						

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

Loop Transaction Totals

Pos: 0100	Repeat: 1
Mandatory	
Loop: CTT	Elements: N/A

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	M	1		Must use
0200	AMT	Monetary Amount Information	O	5		Used

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Mandatory	
Loop: CTT	Elements: 2

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

CTT02	347	Hash Total	O	R	1/10	Used
-------	-----	------------	---	---	------	------

Description: Sum of values of the specified data element. All values in the data element will be summed without regard to decimal points (explicit or implicit) or signs. Truncation will occur on the left most digits if the sum is greater than the maximum size of the hash total of the data element. Example: -.0018 First occurrence of value being hashed. .18 Second occurrence of value being hashed. 1.8 Third occurrence of value being hashed. 18.01 Fourth occurrence of value being hashed. 18E2 Fifth occurrence of value being hashed. ----- 1873 Hash Total

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

AMT

Monetary Amount
Information

Pos: 0200	Max: 5
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Used
Purpose: To indicate the total monetary amount

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage				
AMT01	522	Amount Qualifier Code	O	ID	1/3	Used				
		Description: Code to qualify amount								
		CodeList Summary (Total Codes: 1765, Included: 1)								
		<table><tr><th>Code</th><th>Name</th></tr><tr><td>TT</td><td>Total Transaction Amount</td></tr></table>					Code	Name	TT	Total Transaction Amount
		Code	Name							
TT	Total Transaction Amount									
AMT02	782	Monetary Amount	O	R	1/18	Used				
		Description: Monetary amount								

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	N0	1/10	Must use
Description: Total number of segments included in a transaction set including ST and SE segments						
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Comments:

1. SE is the last segment of each transaction set.